


8 ZONE MICROPHONE and EXTENTION KEY(H-8000RM and H-8000RME)

H-8000RM
H-8000RME



FEATURE:

- The H-8000RM remote paging console is connected with H-8000 through universal industrial standard CAT 5 for zone announcement or communication at a remote and different location from the control center.
- Each controller provides four RJ45 ports for the remote paging console.
- The CAT 5 wiring is not only featured of cost-effective, convenient layout, but also integration of RS 485 communication and audio transmission together.
- Extra DC 24V power supply
- Eight zone selector with state indication.
- Talk and all zone paging swift keys are provided.
- 2 and 4 tones chimes with selector and off switch.
- Volume controls are provided for chime and microphone.
- Full indications include individual zone, all zone, busy, paging, power, output level to provide a direct visualization.

Specification:

Model	H-8000RM/H -8000RME
MIC	Condenser Microphone
Frequency Response	50Hz~18KHz (± 2dB)
S/N Ratio	Better than 75dB
THD	Less than 0.1% at 1KHz,
Signal Output	0.775V/600Ω
Mic Input	5mV/600Ω
Indication	Individual zone, all zone, busy, paging, power, output level indicators
Protection	DC+24V/2A, Revert fuse protection
Power Supply	DC 24V
Power Consumption	5W
Weight	2.5Kg
Dimensions	180x143x52mm

As per our company policy one of the constant Product improvement the right is there for reserved to modify product specifications without prior notice