All In One Amplifier

FEATURE:

- Plug play U disk, FM radio, wireless remote control
- Three microphone inputs. Two auxiliary inputs, and one auxiliary outputs for link.
- Transformer isolated 100V, 70V and 4-16 Ohms speaker outputs.
- A five element LED level meter is provided for quick and easy visual monitoring of the sound level
- Muting function.
- Individual volume control, low and high tone control
- Short circuit protection & alarm
- Individual distributor for each channel
- Series amplifiers of high output power available.
- Out Put for 4zone Audio
- All-in-one public address device combining tuner, MP3 player per-amplifier and power amplifier together with USB port, supports running flash disk or portable hard disk Tuning station saving function after power failure 3 MIC inputs with individual volume control 2 Aux line inputs & 1 line output for additional mixer or amplifier link 1 emergency signal input Built-in chime generator with two types of tone Two levels of priority muting function: MIC1>Chime Bass, treble, and master volume control Output short-circuit protection and alarm function 3 types of speaker output: 100V, 70V, 4-16 Ω

SPECIFICATION:

Model	**HA-40F**	**HA-60F**	**HA-100F**	**HA-150F**	**HA-200F**
Rated Power	40W	60W	100W	150W	200W
Line voltage	70-100V	70-100V	70-100V	70-100V	70-100V
Impedance	4-16 Ω	4-16 Ω	4-16 Ω	4-16 Ω	4-16 Ω
Dimension	380 x 180 x 67	380 x 180 x 67	485 x 360 x 90	485 x 360 x 90	485 x 395 x 90
Model	**HA-280F**	**HA-380F**	**HA-480F**	**HA-680F**	**HA-880F**
Rated Power	280W	380W	480W	680W	880W
Line voltage	70-100V	70-100V	70-100V	70-100V	70-100V
Impedance	4-16 Ω	4-16 Ω	4-16 Ω	4-16 Ω	4-16 Ω
Dimension	485 x 395 x 90	485 x 395 x 90	485 x 445 x 90	485 x 445 x 90	485 x 445 x 90

As per our company policy one of the constant Product improvement the right is there for reserved to modify product specifications without prior notice

HEINRICH

HEINRICH LIMITED, 69 Athlone Road London SW22DU
W: www.heinrichlimited.com E: info@heinrichlimited.com