

# Stero 31 Bands Graphic Equalizer

**BGE315**



## FEATURE:

- Music Type Excellent 31 stereo graphic equalizer, professional level 31 stereo graphic equalizer, which suit for studio recording and performances.
- the KHz of the Mono subwoofer output can be adjusted.
- Each channel can be switched on high cut and low cut filter which can remove the noise, such as local noise and tape hiss.
- Composed of 12 lads of input and output level display which is very accurate, coupled with the input gain control, it can enable you to control level appropriately.
- Operational amplifier with Very low noise can make the tone sound beautiful.
- Equipped with gilded XLR and stereo 6.3mm socket servo balanced input and output port.
- Shielding ring core power transformer can minimize noise.
- High quality components and strong structure.

## SPECIFICATION:

Model	BGE315
Channel	2
Bands	(2x31) 1/3-Octave ISO Spasing (25Hz~20 KHz)
Type	Constant - Q
Travel	20mm (Positive grounded center detent)
Range	± 12dB
Input	Balanced / Unbalanced
Port	XLR and TRS
Impedance	>20K OM balanced
Maximum Level	+21dB
Output	Balanced / Unbalanced
Port	XLR and TRS
Impedance	400 OM balanced 200OM unbalanced
Maximum Level	+21dBu balanced +15dBu unbalanced
	+19 dBu balanced +13dBu unbalanced
Low Cut Filter	10-250Hz, 12dB/ octave
High Cut Filter	3K-40KHz, 12dB/octave
Frequency Response	20-20KHz,(±0.5dB) 10-40KHz(+0/-3dB)
THD & Noise	0.01%
S/N Ratio	96dB
Maximum Power	12W
Universal Line Voltage	AC220V-240V ,50/60Hz
Dimensions	484x156x88mm

As per our company policy one of the constant Product improvement the right is there for reserved to modify product specifications without prior notice