

HDMI CONVERTER (VGA-HDMI)

HT - 8311



DESCRIPTION:

This kind of the Converter is a VGA video converter. It converts VGA input into HDMI and allows PC users to enjoy their larger image on TV. The conversion is along with the R/L audio. It offers solutions for digital entertainment center, HDMI retail and show site. HDTV, STB, DVD and projector factory, noise space and security concerns data center control. Information distribution. conference room presentation, school and corporate training environments.

FEATURE:

This HDMI converter has many features that enable it to perform in a superior manner. Among those features you will find:

- Easy to Use: install in seconds, no need of setting.
- Conversion: It could convert PC's VGA video and R/L audio into complete HDMI.
- HDCP pass-through

HDMI CONVERTER (VGA-HDMI)

SPECIFICATION:

Model	HT-8311
Input video signal	0.5-1.0 v P-P
Input DDC Signal	HDMI 1.2a
Output Video	
VGA	64x480 60Hz 75Hz 800x600 60Hz 75Hz 1024x768 60Hz 75Hz 1280x720 60Hz 75Hz 1280x768 60Hz 75Hz 1280x960 60Hz 75Hz 1280x1024 60Hz 75Hz
DTV/ HDTV	
Frequency	165MHz
Video Amplifier Bandwidth	1.65Gpbs/165MHz
Interlaced (50 & 60 Hz)	480i, 576i, 1080i
Progressive (50 & 60Hz)	480p, 576, 720p, 1080p
Size (W-H-D)	61mm x 21mm x 96mm
Weight (Net	
Limited warranty	
Operating Temperature	0°C~+70°C
Operating Humidity	10%~85%RH (no condensation)
Storage Temperature	-10°C ~ +80°C
External Power Supply	DC 5V
Converter Unit	FCC, CE,
Power Supply	CE, FCC
AC Power Adapter	US standard, UK standard and so on.